



Distribuidor Autorizado En México

COMPACT FM TRANSMITTER ETL3500

MAIN FEATURES

- EASY MAINTENANCE
- WIDE RANGE OF AUDIO INPUTS
- FULLY SELF-PROTECTED & RUGGED DESIGN
- EASY SETUP, OPERATION AND MAINTENANCE
- ETHERNET CONNECTIVITY BASED ON WEB INTERFACE
- FULL REMOTE CONTROL - SNMP
- ADVANCED AUDIO QUALITY
- ULTRA-HIGH SIGNAL TO NOISE RATIO
- EXTREMELY LOW DISTORTION
- POWER SUPPLY HOT PLUG-IN
- HIGH EFFICIENCY UP TO 75%
- EXCELLENT STANDARD FEATURES



ETL SERIES IS A COST-EFFECTIVE FAMILY OF FM TRANSMITTERS MADE IN EUROPE

- ✓ BEST STATE OF THE ART FOR RF PERFORMANCES
- ✓ HIGH QUALITY 3.5 KW IN A 4RU COMPACT SIZE



contacto@comunicacion Wwww.comunica.com.mx 51 394 8953/764 105 5471



Xicotepec de Juárez.
Tierra Negra, Cuetzeo
#8A



GENERAL

Frequency Range	87.5 108 MHz 76
Optional Extended Band	108 MHz 3500W
Power Output	50 Ohm $\pm$ 1 ppm
RF Output Impedance	$\geq$ 80 dB
Frequency Stability	Linear/50/75 μ s
RF Harmonics	EIA 7/8 Flange
Preemphasis	SMA Female
RF Output Connector	$\pm$ 0.25 dB
RF Test Connector	
Power stability	Up to 4000 m a.s.l.
	-10 45°C

ENVIRONMENTAL

Altitude	$\leq$ 95%
Operating Temperature	not condensing Forced Air
Relative Humidity Range	$\leq$ 65 dBA

Cooling Method

Acoustic Noise

AC Input

AC Input	1 or 3 Phases
Power Consumption	4800VA
Cos	$\geq$ 0.95
AC Frequency	47 63 Hz

MECHANICAL

Dimensions (WxLxH)	484x450x178 mm
Weight	22 Kg

